SmartScan Touch INSTALLATION DETAILS

Regular, Teaching and Meeting Versions and ColourActive Touch

NOTE: Distance is reduced if walls are between

SmartScan Touch and Luminaires.





* 922MHz Max. 10m

PROGRAMMING

SmartScan Touch is programmed with the Smart Programmer. This device uses bi-directional infrared to program the SmartScan Touch. Ensure at all times, during use, only one device can be "seen" by the programmer

PROGRAMMER DISPLAY On the first LCD line the actual menu point is displayed. On the second line, the status line, the possible settings for this menu point are shown. During a data transmission, the actual transmission status (as well as any error messages) is shown. Power: 4-off AA/1.5V battery (supplied) catalogue no. LCM 10777SS **T** Only one SmartScan device in view of the programmer

MODIFICATIONS

Thorlux products should not be modified. Any modification may render the product unsafe and will invalidate any Safety/ Approval marks.

MAINTENANCE

The SmartScan Touch should not be subjected to undue mechanical shock or extremes of temperature. Clean only with a clean dry cloth.

PROGRAMMING BUILDING ADDRESS AND GROUP ADDRESS

	FUNCTION	BUTTON	DISPLAY
1	Switch on the Smart Programmer	×	
2	Scroll to the <smart tr=""> menu</smart>	1	<smart tr=""></smart>
3	Select the menu <smart tr=""></smart>		download all <smart only="" tr=""></smart>
4	Scroll to the building setting	1	building: 123 address 1-254
5	To change the address press the (Select) button. (A Star in the upper corner indicates access of the program mode).	√	building: 123* address 1-254
6	Use the scroll buttons, to select the required address	1	building: 123* address 1-254
7	The (Send) button will now, update the chosen parameter in the SmartScan Touch		
8	Scroll to group address	V	group addr: 123 address 1-254
9	Select this parameter. Option name and current status are now displayed on the top line.	V	group addr: 123* address 1-254
10	Use the scroll buttons, to select the required address	1)	group addr: 123* address 1-254
11	The (Send) button will now, update the chosen parameter in the SmartScan Touch		
12	Scroll to RF transmit	V	rf transmit: en enable/disable
13	To change between enable and disable press the (Select) button	\checkmark	rf transmit: en* enable/disable
14	Use the scroll buttons, to select the required function	()	rf transmit: en* enable/disable
15	The (Send) button will now, update the chosen parameter in the SmartScan Touch		
12	To exit the setting mode press (Esc). The new selected value will now be displayed on the first line.	×	group addr: 123 address 1-254
Now all parameters are memorised in the SmartScan Touch			

(Please Note - each SmartScan Touch can have unique parameters if required)

* RF Transmit - can be enabled or disabled from the Smart TR menu. When disabled all radio transmissions are stopped.

NOTE: The SmartScan Touch does not support any other functions from the programmer menu.

	M
Thoriux	RI
LL lighting	e-
	VV
	5

NOTICE TO CONTRACTOR - PLEASE PASS THIS LEAFLET TO THE END MERSE ROAD NORTH MOONS MOAT REDDITCH WORCS. B98 9HH ENGLAND thorlux@thorlux.co.uk www.thorlux.com +44 (0)1527 583200 e-mail: Web:

Australia: Ireland: UAE:

Deutschland: www.thorlux.de www.thorlux.ie www.thorlux.ae

www.thorlux.com.au 🕿 +61 (0)2 9907 1261 ☎ +49 (0)211 6956 0310 ☎ +353 (0)1 460 4608 a +971 (0)2 656 5842

