## INFRA-RED PROGRAMMER FOR SMARTSCAN LUMINAIRES

SPECIFICATION

- Rugged silicone sleeve for improved durability
- Sealed keypad
- Programs operational settings, reads luminaire status and initiates system tests
- Configures wireless communications and mesh network
- Can initiate testing of emergency luminaires
- Can retreave status information from SmartScan emergency luminaires and compatible SmartScan Sensors
- Powered by 4 AA batteries (supplied)

RANGE

DESCRIPTION	CAT. No.	APPROX. kg
SmartScan Programmer	**SS 20211**	0.44

DIMENSIONS

103 42 210